



Distribute One HDMI Source To Ten Displays



EXT-HDMI-1410

One HDMI Input, Ten HDMI Outputs

The 1:10 HDMI Distribution Amplifier is the perfect solution for anyone who needs to send one source of digital high definition video to multiple displays at the same time. It supports all HDMI equipment, such as DVD players and satellite set top boxes and all HDMI displays. HDMI (High-Definition Multimedia Interface) is a digital point to point interface for audio and video signals. In operation, the digital video source is connected to the distribution amplifier on one side. On the other side, ten HDMI outputs are available to be used in part or in full.

Features:

- Connects up to ten HDMI/DVI displays at the same time to one video source
- Allows simultaneous display
- Maintains high resolution video - beautiful, sharp HDTV resolutions up to 1080p, 2k, and computer resolutions up to 1920 x 1200 are easily achieved
- HDMI compliant
- HDCP compliant
- Includes rack ears

How It Works

Simply connect your HDMI video source to the 1:10 HDMI Distribution Amplifier's input using the supplied HDMI cable. Then connect up to ten HDMI displays to the unit's ten HDMI outputs. Once connected and powered, your source will be seen on all ten displays at the same time

Specifications:

- Video Amplifier Bandwidth: 165 MHz
- Input Video Signal: 1.2 Volts p-p
- Input DDC Signal: 5 Volts p-p (TTL)
- Single Link Range: 1080p/1920 x 1200
- HDMI Connector: Type A 19 Pin Female
- Power Supply: 5V DC
- Power Consumption: 20 Watts (max)
- Dimensions: 17"W x 1.75"H x 5.5"D
- Rackmountable: 1U rack space
- Shipping Weight: 8 lbs.